

## An American Company 👴

We produce our products in our 200,000ft<sup>2</sup> facility located in Le Center, Minnesota, equipped with modern engineering, fabrication and assembly capabilities.



#### Cast-Iron Gearcase

Our own WINCO gearcases have proven their strength and durability for over 60 years and will keep doing so into the future.




### Frequency Meter

Large, 3/12" hertz meter ensures the proper output is reached.



### Receptacle Panel



480V & 600V have Anderson connector only

# 50PTOC4

# 55PTOC4

Rugged Design



Brushless Industrial Gen End.



# **SPECIFICATIONS**

## **ELECTRICAL**

|                 |              | <b>STANDBY</b> (150/40C) |                |                | CONTINUOUS (125/40C) |                |               |                    |                            |                                  |
|-----------------|--------------|--------------------------|----------------|----------------|----------------------|----------------|---------------|--------------------|----------------------------|----------------------------------|
| MODEL<br>NUMBER | VOLTS        | WATTS                    | AMPS<br>1.0 PF | AMPS<br>0.8 PF | WATTS                | AMPS<br>1.0 PF | AMPS<br>0.8PF | CIRCUIT<br>BREAKER | INPUT<br>HP <sup>(1)</sup> | MOTOR<br>STARTING <sup>(2)</sup> |
| 50PTOC4-03      | 120/240 1-PH | 50,000                   | 208            | N/A            | 40,000               | 166            | N/A           | 200A               | 100                        | 20 HP                            |
| 50PTOC4-04      | 120/208 3-PH | 50,000                   | 138            | 173            | 42,000               | 116            | 145           | 175A               | 100                        | 22.5 HP                          |
| 50PTOC4-17      | 120/240 3-PH | 50,000                   | 120            | 150            | 42,000               | 101            | 126           | 175A               | 100                        | 22.5 HP                          |
| 55PTOC4-18      | 277/480 3-PH | 55,000                   | 66             | 82             | 46,400               | 55             | 69            | 75AA               | 110                        | 25 HP                            |
| 55PTOC4-21      | 346/600 3-PH | 55,000                   | 52             | 66             | 46,400               | 44             | 55            | 75A                | 110                        | 25 HP                            |

NOTES: (1)Required HP at PTO of tractor for full rated power. Each 2 HP equals approximately 1kW of electric power. (2) Code G capacitor motor.

## 50-55PTO

| PTO INPUT SPEED  | 540 RPM<br>1000 RPM        |
|------------------|----------------------------|
| INPUT SHAFT SIZE | 1 3/8" 6-SPLINE            |
| FREQUENCY METER  | STANDARD                   |
| NEUTRAL BONDED   | YES                        |
| GROUND LUG       | YES                        |
| GEARCASE OIL     | SAE 85W-90-140 - 0.88 PINT |

# **SHIPPING**

| SHIPPING DIMENSIONS (L x W x H) | 46" x 29" x 28" |
|---------------------------------|-----------------|
| SHIPPING WEIGHT                 | 745 LBS         |
| FREIGHT CLASS                   | 65              |


# **OPTIONAL ACCESSORIES**

| PTO TRAILER           | TDM80           |
|-----------------------|-----------------|
| PTO DRIVE SHAFT       | 1 3/8" 6-SPLINE |
| THREE POINT-HITCH KIT | TPH260          |
| GEARCASE UPGRADE      | 1000 RPM        |
| TRANSFER SWITCH       | VARIOUS         |


## **GEN END**

| GLIVLIVD                                     |                          |
|--|--------------------------|
| SINGLE PHASE <sup>(1)</sup>                  | 4 LEAD                   |
| WINDING NUMBER                               | 06                       |
| THREE PHASE                                  | 12 LEAD                  |
| WINDING NUMBER                               | 311                      |
| AVR  | AS440                    |
| VOLTAGE REGULATION                           | +/- 1%                   |
| TOTAL HARMONIC DISTORTION                    | < 5%                     |
| GENERATOR SPEED                              | 1800 RPM                 |
| STATOR WINDING                               |                          |
| SINGLE PHASE                                 | SINGLE LAYER CONCENTRIC  |
| THREE PHASE                                  | DOUBLE LAYER CONCENTRIC  |
| ROTOR  | 2/3 PITCH                |
| TELEPHONE INTERFERENCE                       | TIF < 50                 |
| INSULATION                                   | CLASS H                  |
| PROTECTION                                   | IP23                     |
| BRUSHLESS                                    | YES                      |
| EFFICIENCY                                   | SINGLE PHASE 0.1 PF 84.9 |
|  | THREE PHASE 0.8 PF 89.2  |
| 120 VOLT RECEPTACLES <sup>(2)</sup>          | (2) NEMA 5-20 20A        |
| 240 VOLT RECEPTACLES <sup>(2)</sup>          | (1) NEMA 6-50 50A        |
| FULL POWER ANDERSON                          |                          |
| SINGLE PHASE                                 | 350 AMPS                 |
| THREE PHASE                                  | 175 AMPS                 |
| UNIT WARRANTY <sup>(3)</sup>                 | 3 YEARS                  |
| NOTES: (1) Unity (1.0) nower factor (2), 480 | V and 600V have Anderson |

NOTES: (1) Unity (1.0) power factor (2) 480V and 600V have Anderson receptacles only. (3) For more generator warranty, see operator's manual.







Specifications are subject to change without notice.

SP-205/D PG 2

0